

Windows XP & Office 2003 Checklist

SUMMARY

This paper will go through a setup checklist when using iQsystem 6.1x

PROCEDURE

Please if you have a firewall or Proxy use the below information.

Below is a list of the critical items that must be considered when configuring a proxy server or firewall-

- The domain certiport.com needs to be accessible.
- The following IP addresses **192.41.91.75, 192.41.91.74, 192.41.91.76, 192.41.91.77 and 206.81.137.18** need to have full access through ports 80 (HTTP) and 443 (HTTPS)
- HTTP and HTTPS redirects needs to be permitted (these are all completed within the certiport.com domain).
- Please DO NOT block soap HTTP traffic

6.1x iQsystem OS & Environmental Requirements

- Pentium III with 750 MHZ or better.
- 256 MB RAM.
- 500 MB free disk space after Windows & Office has been installed.
- 17 inch monitor with a screen resolution of 1024 x 768 or higher.
- The user account used for exam must have **FULL** local admin rights.
- A local or network printer must be installed for printing the result sheets.
- Format the system drive and install Windows XP Pro to the C: Drive.
- Install Windows XP SP2.
- Create or use a user with Administrative Rights (User must be logged in as an Administrator when installing and running exams).
- Install Microsoft Office 2003 Professional SP2, Office 2003 Enterprise, or Office 2003 Premier (Standard, Home, and Business versions are not supported).
 1. Install to the **default** directory.
 2. Install on the same drive as the Operating System.
 3. Choose "**Complete Installation**".
 4. Select "Run all from my computer".
 5. Only install Disk to C: drive.
- Install Adobe Flash player
- Ensure that you have an internet connection at least 156 KBPS or better.
- Open each Office application and ensure each has been activated.
- When launching Outlook for the 1st time
 1. Do not create an email account
 2. Accept all other default values
- Ensure that Internet Explore is version 6.0 with SP1 or higher.

iQsystem installation considerations

- Ensure Internet Explorer can access the Certiport Web Site.
- Install iQsystem from CD or the Certiport website.
- Log into iQsystem Tools.
 1. Complete iQupdate. (iQsystem 6.1x should be the most current version.)
 2. Run a configuration exam to check the install.

Certiport Customer Support

Phone: (801) 847-3100

Toll Free: (888) 999-9830

eSupport: www.certiport.com

NOTE: Your feedback is always welcome; it will help the Certiport Operations team serve you better.

© 2007 Certiport, Inc.